

SAT-Multischalter 9/8

Best.Nr. 570 619

			
ITEM		TYP	REMARK
Frequency response		47-2150MHz	
Inputs		8 SAT + 1 Terr	F connectors
Outputs		8	F connectors
Gain	Terr 47-862MHz		4dB
	Sat 950-2150MHz		0dB
Return Loss	Terr in 47-862MHz		11dB
	Sat in 950-2150MHz		10dB
	Terr out 47-862MHz		8dB
	Sat out 950-2150MHz		8dB
Isolation	LNB-LNB 950-2150MHz		35dB
	OUT-OUT	Terr 47-862MHz	26dB
		Sat 950-2150MHz	30dB
	H/V	Sat 950-2150MHz	26dB
Switching voltage		15 ± 1V	
Switching commands		13V, 18V, 13V/22KHz, 18V/22KHz, DiSEqC2.0	